

REF. NO.	PART DESCRIPTION	AMPEX PART NO.
R47	RESISTOR, Fixed: composition; 22K ohms; ±10%; 2 watt; MIL-R-11A: RC42GF223K	041-216
R48	RESISTOR, Fixed: composition; 150K ohms; ±10%; 1/2 watt; MIL-R-11A: RC20GF154K	041-074
R49	(Same as R45)	041-374
R50	(Same as R46)	041-081
R51	(Same as R47)	041-216
R52	(Same as R48)	041-074
R53	POTENTIOMETER, Dual: ganged; 25K ohms	96928-01
R54	RESISTOR, Fixed: composition; 24K ohms; ±5%; 1/2 watt; MIL-R-11A: RC20GF243J	041-369
R55	(Same as R54)	041-369
R56	RESISTOR, Fixed: wirewound; 2 ohms; ±10%; 5 watt; Tru-Ohm Type X-60	043-990
R57	RESISTOR, Fixed: composition; 2.2K ohms; ±10%; 1/2 watt; MIL-R-11A: RC20GF222K	041-052
R58	(Same as R57)	041-052
S1	SWITCH, Mixer	96925-01
S2	(Same as S1)	96925-01
S3	SWITCH, Mixer	96926-01
S4	(Same as S3)	96926-01
S5	(Same as S3)	96926-01
S6	(Same as S3)	96926-01
S7	SWITCH, Slide: DPDT	96139-02
S8	SWITCH, Toggle: SPST; paddle handle; 3 amp; Circle F Part No. 1887-L4P	120-999
T1	TRANSFORMER, Microphone	96908-01
T2	(Same as T1)	96908-01
T3	(Same as T1)	96908-01
T4	(Same as T1)	96908-01
T5	TRANSFORMER, Power	96144-01
TS1	STRIP, Terminal: barrier; 6 terminals; Cinch- Jones Part No. 6-140Y	180-111
V1	TUBE, Electron: 9 pin; miniature; AmpereX Type EF86/6267	012-098
V2	(Same as V1)	012-098
V3	(Same as V1)	012-098
V4	(Same as V1)	012-098
V5	(Same as V1)	012-098
V6	(Same as V1)	012-098
V7	TUBE, Electron: 9 pin; miniature; AmpereX Type 12AU7	012-107
	INDICATOR, Reset	50735-02
	PLUG ASSEMBLY, Dummy	17420-01
	KNOB, Key tab (MX-10)	96922-01
	KNOB, Key tab (MX-35)	96922-02
	CORD, Power Input	084-004
	POST, Fuse: Littelfuse Part No. 342012	085-001
	SHIELD, Tube: 9 pin; Cinch-Jones Part No. 9S2	160-012
	KNOB, Medium dark grey (MX-10)	96585-01
	KNOB, Black (MX-35)	230-003
	KNOB, Light grey (MX-10)	96585-02
	KNOB, Black (MX-35)	230-004
	SOCKET, Tube: 9 pin; Cinch-Jones Part No. 53F12621	150-020
	CONNECTOR, Plug: female; 3 contact; Cannon Part No. XL-3-11	144-003